

RTR0 LED RETROFIT LAMPS

120VAC OPERATION, 1.2W PER LAMP
 SCREW-IN BASE

The AimLite RTR0 exit sign replacement lamp kit provides exceptional energy and maintenance savings over traditional incandescent type lamps. Each RTR0 lamp consumes just 1.2W of AC power and is designed utilizing long-life maintenance-free LEDs. The twenty-six high brightness LEDs are arranged in a “U” shape in order to optimize the light distribution. The thin-line LED housing is made from an advanced technopolymer that can be rotated to align with the faceplate of the exit sign.



FEATURES & SPECIFICATIONS

CONSTRUCTION

- Lightweight and durable white technopolymer housing construction
- Housing can be rotated 180° in either direction to align with exit sign faceplate
- Integral candelabra base standard
- Optional screw-in bases available for:

- Intermediate Base
- DC Bayonet Base
- Slim design to allow installation into narrow width exit signs

ELECTRICAL

- 120VAC 60Hz input
- 1.1W power consumption per lamp
- 26 High brightness LEDs per lamp
- Integral current limiting and surge absorbing capacitors insure flicker free, long-life operation

ORDERING GUIDE

RTR0 —

SERIES	BASE TYPE
RTR0	U - UNIVERSAL (KIT INCLUDE CANDELABRA, INTERMEDIATE & DOUBLE CONTACT BAYONET)

Data is based upon tests performed in a controlled environment. Actual performance can vary depending on operating conditions. All products are subject to change or may be discontinued any time without notice.